



BEAMZ
MADE
EAZY

150.750 V1.0

STARCOLOR72B

QUICK START GUIDE

CONTROL MENU

| MENU | DESCRIPTION | | | |
|-------------------|---------------------------------------|---|--|---------------------|
| DMX ADDR | A001-A512 | DMX mode, press up or down to adjust address code | | |
| MACRO | Auto Color | | | |
| | Auto Fade | | | |
| | Auto Sudden | Press Enter --UP/DOWN to adjust speed from 01-16 | | |
| | Auto Strobe | | | |
| WIFI | Press Enter shows LED_xxx | Controlled by mobile phone APP | | |
| MANUAL | Custom Color | Red 0-255 | Dimming static color | |
| | | Green 0-255 | | |
| | | Blue 0-255 | | |
| | | White 0-255 | | |
| | | Amber 0-255 | | |
| | | Strobe 0-255 | | |
| | Static | Color: 01 | 27 kinds static color | |
| | | | | |
| | SETTING | DMX Channel | 5CH | 5 DMX channels mode |
| | | | 7CH | 7 DMX channels mode |
| 9CH | | | 9 DMX channels mode | |
| DMX Signal State | | Black | Give up signal if DMX signal disconnect | |
| | | Hold | Hold signal if DMX signal disconnect | |
| 2.4g Wireless | | Wireless | ON/OFF | |
| | | Mode | Transmit/Receive | |
| | | Reset | No/YES | |
| | | Connect | No/YES | |
| Infrared | | ON/OFF | Enable or disable infrared remote | |
| Display Backlight | | 0-100% | LCD background | |
| LCD Display | | 1. Always ON | LCD wake up | |
| | | 2. 10s | 10/30/45/60 seconds without operation, LCD enters sleep mode | |
| | | 3. 30s | | |
| | | 4. 45s | | |
| | | 5. 60s | | |
| Restore Factory | | Load default data | Password: 8888 | |
| Limit Light | | Adjust working current | Password: xxxx, operated only by manufacturer | |
| Battery | | ON/OFF | Show battery capacity on display | |
| Background Color | | 00-08 | Different LCD back ground color | |
| Menu Lock | ON/OFF | Press up/down together for 4 second to release lock | | |
| HELP | Name: Starcolor72B | | | |
| | Version:V2.x | Software version | | |
| | DMX Channel: Xch | DMX channel mode | | |
| | Run Time: x:xx | Work time | | |
| | User Time | Work time | | |
| | QR code for download mobile phone app | Press UP or DOWN to show this code | | |

DMX CHANNELS

5 CHANNELS

| CHANNEL | FUNCTION | VALUE | DESCRIPTION |
|---------|----------|---------|---------------|
| 1 | | 000-255 | Dimming Red |
| 2 | | 000-255 | Dimming Green |
| 3 | | 000-255 | Dimming Blue |
| 4 | | 000-255 | Dimming White |
| 5 | | 000-255 | Dimming Amber |

7 CHANNELS

| CHANNEL | FUNCTION | VALUE | DESCRIPTION |
|---------|----------|---------|--------------------------|
| 1 | | 000-255 | Master dimmer |
| 2 | | 000-255 | Strobe from slow to fast |
| 3 | | 000-255 | Dimming Red |
| 4 | | 000-255 | Dimming Green |
| 5 | | 000-255 | Dimming Blue |
| 6 | | 000-255 | Dimming White |
| 7 | | 000-255 | Dimming Amber |

9 CHANNELS

| CHANNEL | FUNCTION | VALUE | DESCRIPTION |
|---------|----------|---------|----------------------------------|
| 1 | | 000-255 | Master dimmer |
| 2 | | 000-255 | Dimming Red |
| 3 | | 000-255 | Dimming Green |
| 4 | | 000-255 | Dimming Blue |
| 5 | | 000-255 | Dimming White |
| 6 | | 000-255 | Dimming Amber |
| 7 | | 000-010 | No function |
| | | 011-255 | Strobe from slow to fast |
| | | 000-008 | No function |
| | | 009-060 | Static color |
| | | 061-120 | Jump mode |
| 8 | | 121-180 | Puls mode |
| | | 181-255 | Fade mode |
| | | | Speed for channel 8 |
| 9 | | 001-255 | Static color when channel 8=9-50 |



BEAMZ

YOUR FUTURE
YOUR SKILLS
YOUR PLATFORM
YOUR PARTY
YOUR EVENT



offers a wide range of high performance lighting equipment and related accessories for the rental, entertainment and architectural lighting markets. BeamZ Pro stands for performance, innovation and value pricing!

