

BEAMZ MADE EAZY

155.102 V1.0

BTK100C QUICK START GUIDE

CONTROL MENU

MENU		DESCRIPTION	
DMXØ6 OK	001-512	"OK" represents signal received;"!!" represents no signal received;"DMX06" represents current channel is channel 6;"DMX02" represents current channel is channel 2.	
DMX CHX	06CH	06ch: Channel 6	
	02CH	02ch: Channel 2	
WORK MODE	DMX	Dmx512 console dimming mode	
	Rotate	Potentiometer dimming mode	
	Manual	Manual dimming mode	
LED CCT	4000K	Under manual mode, the CCT selected 2800k → 6000k	
DIMMER	100%	Under manual mode, the dimmer selected $000\% \rightarrow 100\%$	
MM	100%	Under rotate mode, console Warm White to sletect low CCT luminance (0%-100%)	
CM	100%	Under rotate mode, console Cool White to sletect high CCT luminance (0%-100%)	
LED MODE	Smooth / Fast	Smooth: smooth dimming Fast: fast dimming	
LCD BACK	Off / Open	Off: display turned off automatically after 30s without button operation Open: display always on	
FAN MODE	High / Auto	High: cooling fan is working at high speed Auto: cooling fan is working in intelligent mode, the corresponding operation will be turned on automatically when reaching the appropriate temperature.	
LED TEMP	060C	Temperature in Celsius	

DMX CHANNELS

6 CHANNELS

1 DIMMING 2 STROBE	000-255 000-255	$0 \rightarrow 100\%$ Slow \rightarrow Fast
2 STROBE		Slow → Fast
3 LOW CCT	000-255	0 → 100%
4 HIGH CCT	000-255	0 → 100%
5 0	000-039	Standard CCT
2800K	040-079	
3200K	080-119	
4000K	120-159	
4800K	160-199	
5600K	200-239	
6000K	240-255	
6 LOW CCT→HIGH CCT	000-255	No polar CCT

2 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	DIMMING	000-255	0 → 100%
2	LOW CCT→HIGH CCT	000-255	No polar CCT

YOUR FUTURE YOUR SKILLS YOUR PLATFORM YOUR PARTY YOUR EVENT

≥beamZ^{Pro}

offers a wide range of high performance lighting equipment and related accessories for the rental, entertainment and architectural lighting markets. BeamZ Pro stands for performance, innovation and value pricing!