




**BEAMZ**  
**MADE**  
**EAZY**

150.164 150.167 V1.0

**STARCOLOR54**  
**STARCOLOR54 TOUR**  
**QUICK **START** GUIDE**

# CONTROL MENU

If the display is in standby, unlock it:



MENU			DESCRIPTION	
MENU	Dimmer ALL	000-255	Master dimmer	
	Balance	Dimmer Red	000-255	Color Dimmer
		Dimmer Green	000-255	Color Dimmer
		Dimmer Blue	000-255	Color Dimmer
		Key lock	Off	Activate key lock yes/no
		On		
	Remote	Off		Activate IR remote yes/no
		ON		
	SET UP	Display	30S	Display sleep mode or on
			ON	
Reset			Reset mode	
Refresh rate		600Hz		Refresh rates
		1200Hz		
		2400HZ		
		4800HZ		
MAX temp	Choose between 30 - 70	Choose max temp		
INFO	Software Ver ***		Shows software version	
	Working times *****H *M		Shows Working hours	
	RDM:*****		Shows RDM address	
DMX ADDRESS	000-512	Select a DMX Channel		
CHANNEL MODE	3CH,5CH,8CH,13CH	Select a Channel mode		
DIM CURVE	Curv1 (2-3-4)	Select a Dimcurve		
DMX STATE	Hold/ Blackout	Select what to do when there is no DMX signal input.		
SLAVE MODE	Slave	Select slave mode		
AUTO MODE	Speed	01-31	Select speed auto mode	
	Auto	01-10	Select different auto mode	
MANUAL MODE	Red	000-255	Adjust dimming	
	Green	000-255	Adjust dimming	
	Bleu	000-255	Adjust dimming	
	Strobe	00-20	Adjust strobe	
	Color	01-55	Adjust Color	

# DMX CHANNELS

## 3 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	Red	000-255	Dimmer
2	Green	000-255	Dimmer
3	Blue	000-255	Dimmer

## 5 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	Dimmer	000-255	Master dimmer
2	Red	000-255	Dimmer
3	Green	000-255	Dimmer
4	Blue	000-255	Dimmer
5	Strobe	000-009	Led blue
		010-255	Strobe (from slow to fast)

## 8 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	Dimmer	000-255	Master dimmer
2	Red	000-255	Dimmer
3	Green	000-255	Dimmer
4	Blue	000-255	Dimmer
5	Strobe	000-009	No function
		010-255	Strobe (from slow to fast)
6	Static Color	000-009	No function
		010-174	Static color
		175-189	3200k
		190-204	5600k
		205-219	6500k
		220-234	8500k
		235-249	10000k
		250-255	Default
7	Auto program	000-020	No function
		021-030	Auto 1
		031-040	Auto 2
		041-050	Auto 3
		051-060	Auto 4
		061-070	Auto 5
		071-080	Auto 6
		081-090	Auto 7
		091-100	Auto 8
		101-110	Auto 9
		111-120	Auto 10
8	Auto speed	121-255	Reserved
		000-255	Speed slow to fast

## 13 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	Dimmer	000- 255	Master dimmer
2	Dimmer fine	000- 255	Fine control of master dimmer
3	Red	000- 255	Dimmer
4	Red fine	000- 255	Fine control of Red dimmer
5	Green	000- 255	Dimmer
6	Green fine	000- 255	Fine control of Green dimmer
7	Blue	000- 255	Dimmer
8	Blue fine	000- 255	Fine control of Blue dimmer
9	Strobe	000-009	Leds on
		010-255	Strobe (from slow to fast)
		000-009	No function
		010-174	Static color
		175-189	3200k
		190-204	5600k
		205-219	6500k
		220-234	8500k
		235-249	10000k
10	Static color	250-255	Default
		000-020	No function
		021-030	Auto 1
		031-040	Auto 2
		041-050	Auto 3
		051-060	Auto 4
		061-070	Auto 5
		071-080	Auto 6
		081-090	Auto 7
		091-100	Auto 8
11	Auto mode	101-110	Auto 9
		111-120	Auto 10
		121-255	Reserved
		000-255	Speed slow to fast
		000-015	Null
		016-075	Dimming curve 1
12	Auto speed	076-135	Dimming curve 2
		136-195	Dimming curve 3
		196-255	Dimming curve 4
		000-015	Null
13	Dimming curve	016-075	Dimming curve 1
		076-135	Dimming curve 2
		136-195	Dimming curve 3
		196-255	Dimming curve 4



A series of horizontal dotted lines for writing, spanning the width of the page.



A series of horizontal dotted lines for writing, spanning the width of the page.





A series of horizontal dotted lines for writing, spanning the width of the page.



# BEAMZ

**YOUR FUTURE**  
**YOUR SKILLS**  
**YOUR PLATFORM**  
**YOUR PARTY**  
**YOUR EVENT**



offers a wide range of high performance lighting equipment and related accessories for the rental, entertainment and architectural lighting markets. BeamZ Pro stands for performance, innovation and value pricing!

