



BEAMZ
MADE
EAZY


150.758 V1.0

BWA410 MKII

QUICK START GUIDE

CONTROL MENU

If the display is in standby, unlock it:



MENU		DESCRIPTION
AXXX	001-512	DMX address 8 Channel mode / Slave function
DXXX	001-512	DMX address 4 Channel mode / Slave function
CLXX	01-32	Static colors selection
CCXX	01-99	Color change speed from slow to fast
EEXX	01-99	Fade speed from slow to fast
FFXX	01-99	Mutation speed from slow to fast
VER2		Software version
LED	Led	On/Off
TEST	rED	Color automatic cycle test
	GrEE	
	bLuE	
	Whit	
	Full	
RXXX	rxxx	Red 000-255
	Gxxx	Green 000-255
	bxxx	Blue 000-255
	Uxxx	White 000-255

DMX CHANNELS

4 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	RED	000-255	Red dimming
2	GREEN	000-255	Green dimming
3	BLUE	000-255	Blue dimming
4	WHITE	000-255	White dimming

8 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	DIMMER	000-255	Master dimming
2	RED	000-255	Red dimming
3	GREEN	000-255	Green dimming
4	BLUE	000-255	Blue dimming
5	WHITE	000-255	White dimming
6	STROBE	000-009	No strobe
		010-255	Strobe speed from slow to fast
7	MACRO	000-009	Channel 2 - 5 effective
		010-049	Colour selection (channel 8 for select the colour)
		050-089	Colour jump (channel 8 for the speed)
		090-129	Colour fade (channel 8 for the speed)
		130-199	Colour mutation (channel 8 for the speed)
		200-255	No function
8	MACRO SPEED	000-255	Macro speed channel 7



BEAMZ

YOUR FUTURE
YOUR SKILLS
YOUR PLATFORM
YOUR PARTY
YOUR EVENT



offers a wide range of high performance lighting equipment and related accessories for the rental, entertainment and architectural lighting markets. BeamZ Pro stands for performance, innovation and value pricing!

