



**BEAMZ**  
**MADE**  
**EAZY**

150.658 V1.4

**KRATOS**

**QUICK START GUIDE**

# CONTROL MENU

MENU		DESCRIPTION	
<b>DMX MODE</b>	001-512	DMX address setting and Receive mode	
<b>SHOW</b>	Auto	Auto Mode:000-068 68 kinds of Auto effect	
		Speed:001-016 1-16 from slow to fast on speed setting	
		Color:000-015 Color setting, <b>0</b> for automatic color change, a total of 15 colors	
	Sound	Sound Mode:001-004 4 sound control modes optional	
		Sens:001-100 Sound sensitivity setting	
		Color :000-015 Color setting, <b>0</b> for automatic color change, a total of 15 colors	
	Static Color	Dimmer:000-255 Overall dimming	
		Strobe:000-255 Strobe	
		Red:000-255 Red dimming	
		Green:000-255 Green dimming	
		Blue:000-255 Blue dimming	
	Color	White:000-255 White dimming	
		Built in static color	Red           Cyan           Blue+W
			Green       Purple       Yellow+W
Blue       Warm       Cyan+W			
White       Red+W       Purple+W			
Yellow       Green+W       Full			
CCT	Color temperature	2800K, 3000K, 3200K, 3500K, 3800K, 4000K, 4500K, 5000K, 5600K, 6000K, 6500K, 7000K, 7500K, 8000K, 8500K, 9000K, 9500K, 10000K	
Wifi		On the phone, connect WIFI address "Led_XXX" and turn on the APP <b>【LED LAMP】</b> to control	
DMX channel	2CH/4CH/6CH/11CH/32CH/64CH/128CH	7 DMX channel modes	
DMX fail	HOLD / Blackout	Status of light fixture after DMX fail	
Display reverse	OFF / ON	Display Reverse OFF / ON	
Display on time	ON / 30S / 60S	Display start time	
Menu lock	OFF / ON	When Menu Lock is ON, the button will be locked after 30 seconds without any operation, and press the UP+DOWN button for 5 seconds to unlock.	
IR remote	OFF / ON	Infrared remote control OFF / ON	
<b>SET</b>	Wireless 2.4g	Wireless       OFF / ON	Wireless DMX OFF / ON
		Connect       NO / YES	
		Reset       NO / YES	
		Mode       Receive / Transmit	
Factory set	1.Red	000-255	Limit the red brightness value, factory default value is 220
	2.Green	000-255	Limit the green brightness value, factory default value is 220
	3.Blue	000-255	Limit the blue brightness value, factory default value is 220
	4.White	000-255	Limit the white brightness value, factory default value is 220
	5.State	Single / Whole	Single: only the current color, Whole: full color working
	6.T.Limit	040-100	Set the start temperature of temperature protection
Factory reset	NO/ YES	YES: Restore factory settings	
<b>INFO</b>	Name	Kratos	
	Version	Vxxx	Software version

# DMX CHANNELS

## 2 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	OVERALL DIMMER	000-255	Linear dimming from 0-100%
2	NO FUNCTION	000-010	CCT
	2800K	011-024	
	3000K	025-038	
	3200K	039-052	
	3500K	053-066	
	3800K	067-080	
	4000K	081-094	
	4500K	095-108	
	5000K	109-122	
	5600K	123-136	
	6000K	137-150	
	6500K	151-164	
	7000K	165-178	
	7500K	179-192	
	8000K	193-206	
	8500K	207-220	
	9000K	221-234	
	9500K	235-248	
	10000K	249-255	

## 4 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	RED DIMMER	000-255	Linear dimming from 0-100%
2	GREEN DIMMER	000-255	Linear dimming from 0-100%
3	BLUE DIMMER	000-255	Linear dimming from 0-100%
4	WHITE DIMMER	000-255	Linear dimming from 0-100%

## 6 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	OVERALL DIMMER	000-255	Linear dimming from 0-100%
2	STROBE	000-010	No function
		011-255	From slow to fast (1HZ-20HZ)
3	RED DIMMER	000-255	Linear dimming from 0-100%
4	GREEN DIMMER	000-255	Linear dimming from 0-100%
5	BLUE DIMMER	000-255	Linear dimming from 0-100%
6	WHITE DIMMER	000-255	Linear dimming from 0-100%

## 11 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	OVERALL DIMMER	000-255	Linear dimming from 0-100%
2	STROBE	000-010	no function
		011-255	From slow to fast(1HZ-20HZ)
3	STATIC MACRO	000-010	No function
		011-255	17 values for each color
4	MACRO BACKGROUND COLOR	000-016	No function
		017-255	17 values for each color
5	MACRO BACKGROUND COLOR BRIGHTNESS	000-255	Linear dimming from 0-100%
6	MACRO	000-010	No function

		011-220	3 values for each macro effect
		221-228	Sound control mode 1
		229-236	Sound control mode 2
		237-244	No function
		245-255	Sound control mode 3
7	MACRO SPEED	000-255	From slow to fast
8	RED DIMMER	000-255	Linear dimming from 0-100%
9	GREEN DIMMER	000-255	Linear dimming from 0-100%
10	BLUE DIMMER	000-255	Linear dimming from 0-100%
11	WHITE DIMMER	000-255	Linear dimming from 0-100%

### 32 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	RED 1 DIMMER	000-255	Linear dimming from 0-100%
2	GREEN 1 DIMMER	000-255	Linear dimming from 0-100%
3	BLUE 1 DIMMER	000-255	Linear dimming from 0-100%
4	WHITE 1 DIMMER	000-255	Linear dimming from 0-100%
...	.....	...	...
29	RED 8 DIMMER	000-255	Linear dimming from 0-100%
30	GREEN 8 DIMMER	000-255	Linear dimming from 0-100%
31	BLUE 8 DIMMER	000-255	Linear dimming from 0-100%
32	WHITE 8 DIMMER	000-255	Linear dimming from 0-100%

### 64 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	RED 1 DIMMER	000-255	Linear dimming from 0-100%
2	GREEN 1 DIMMER	000-255	Linear dimming from 0-100%
3	BLUE 1 DIMMER	000-255	Linear dimming from 0-100%
4	WHITE 1 DIMMER	000-255	Linear dimming from 0-100%
...	.....	...	...
61	RED 16 DIMMER	000-255	Linear dimming from 0-100%
62	GREEN 16 DIMMER	000-255	Linear dimming from 0-100%
63	BLUE 16 DIMMER	000-255	Linear dimming from 0-100%
64	WHITE 16 DIMMER	000-255	Linear dimming from 0-100%

### 128 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	RED 1 DIMMER	000-255	Linear dimming from 0-100%
2	GREEN 1 DIMMER	000-255	Linear dimming from 0-100%
3	BLUE 1 DIMMER	000-255	Linear dimming from 0-100%
4	WHITE 1 DIMMER	000-255	Linear dimming from 0-100%
...	.....	...	...
125	RED 32 DIMMER	000-255	Linear dimming from 0-100%
126	GREEN 32 DIMMER	000-255	Linear dimming from 0-100%
127	BLUE 32 DIMMER	000-255	Linear dimming from 0-100%
128	WHITE 32 DIMMER	000-255	Linear dimming from 0-100%



A series of horizontal dotted lines for writing, spanning the width of the page.



A series of horizontal dotted lines for writing, spanning the width of the page.



A series of horizontal dotted lines spanning the width of the page, intended for writing or drawing.



# BEAMZ

**YOUR FUTURE**  
**YOUR SKILLS**  
**YOUR PLATFORM**  
**YOUR PARTY**  
**YOUR EVENT**



offers a wide range of high performance lighting equipment and related accessories for the rental, entertainment and architectural lighting markets. BeamZ Pro stands for performance, innovation and value pricing!

