



BEAMZ
MADE
EAZY

151.511 V1.1

BAC552Z

QUICK START GUIDE

CONTROL MENU

MENU		DESCRIPTION
A001	A001-A512	Press Up or Down to modify address codes (A001-A512), press ENTER to Save
CH10	CH10-CH18	Press Up or Down to modify Channels CH10,CH18, press ENTER to Save
N000	N000-N084	Press Up or Down to choose built-in effects (N000- N084), default N007, press ENTER to Save
S000	S000-S255	Press Up or Down to modify speed (S000- S255), default S024, press ENTER to save
S0UD	Soud	Sound-activated
R000	R000-R255	Press Up or Down to adjust red brightness (R000- R255), press ENTER to save
G000	G000-G255	Press Up or Down to adjust green brightness (G000- G255), press ENTER to save
B000	B000-B255	Press Up or Down to adjust blue brightness (B000- B255), press ENTER to save
W000	W000-W255	Press Up or Down to adjust white brightness (W000- W255), press ENTER to save
M000	M000-M2555	Zoom motor
T000	T000-T100	Display temperature
FACTORY SETTINGS	R032-R255	Press Up or Down to adjust Red LED current (R032-R255), press ENTER to save
	G032-G255	Press Up or Down to adjust Green LED current (G032-G255), press ENTER to save
	B032-B255	Press Up or Down to adjust Blue LED current (B032-B255), press ENTER to save
	W032-W255	Press Up or Down to adjust White LED current (W032-W255), press ENTER to save
	M000-M255	Zoom motor current
	FA-N	Fan set: FA-N Light on indicates the fan is on, FA-Y Starts the fan when it reaches the set temperature protection point, press ENTER to save
	T040-T105	Press Up or Down to set temperature protection point (40°C-105°C), press ENTER to save
	Send	Press Up or Down to send factory settings parameters to all other fixtures connected. Confirm sending by pressing the menu button for 3 seconds, otherwise press Confirm to deny the sending.

DMX CHANNELS

10 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1		000-255	Zoom
2		000-255	Dimmer
3		000-255	Strobe
4		000-255	R Red linear dimming
5		000-255	G Green linear dimming
6		000-255	B Blue linear dimming
7		000-255	W White linear dimming
8		000-255	Mode
9		000-255	Speed
10		000-249	No function
		250-255	Reset all

18 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1		000-255	Zoom
2		000-255	Dimmer
3		000-255	Strobe
4		000-255	The first circle of red LED
5		000-255	The first circle of green LED
6		000-255	The first circle of blue LED
7		000-255	The first circle of White LED
8		000-255	The second circle of red LED
9		000-255	The second circle of green LED
10		000-255	The second circle of blue LED
11		000-255	The second circle of White LED
12		000-255	The third circle of red LED
13		000-255	The third circle of green LED
14		000-255	The third circle of blue LED
15		000-255	The third circle of White LED
16		000-255	Mode
17		000-255	Speed
18		000-249	No function
		250-255	Reset all



BEAMZ

YOUR FUTURE
YOUR SKILLS
YOUR PLATFORM
YOUR PARTY
YOUR EVENT

 **beamZ^{Pro}**

offers a wide range of high performance lighting equipment and related accessories for the rental, entertainment and architectural lighting markets. BeamZ Pro stands for performance, innovation and value pricing!



BEAMZLIGHTING.COM