



BEAMZ
MADE
EASY

156.105 V1.0

EZYBAR3

QUICK START GUIDE

CONTROL MENU

MENU	DESCRIPTION
A001-A512	DMX512 address setting
d000- d099	Master dimming
d100- d199	LED1 Warm white linear dimming
d200- d299	LED1 Cool white linear dimming
d300- d399	LED2 Warm white linear dimming
d400- d499	LED2 Cool white linear dimming
d500- d599	LED3 Warm white linear dimming
d600- d699	LED3 Cool white linear dimming
St00- 99	Strobe from slow to fast
Su00- 99	Sound
Ju00- Ju99	Jump from slow to fast
Fa00- Fa99	Fade from slow to fast
CT0	Knob control, warm white and cool white dimming

REMOTE CONTROL



DMX CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	Master dimming	000-255	Master dimming, 0-100%
2	LED 1 Dimming	000-255	LED1 Warm white dimmer 0-100%
3		000-255	LED1 Cool white dimmer 0-100%
4	LED 2 Dimming	000-255	LED2 Warm white dimmer 0-100%
5		000-255	LED2 Cool white dimmer 0-100%
6	LED 3 Dimming	000-255	LED3 Warm white dimmer 0-100%
7		000-255	LED3 Cool white dimmer 0-100%



BEAMZ

YOUR FUTURE
YOUR SKILLS
YOUR PLATFORM
YOUR PARTY
YOUR EVENT



is a leading developer of lighting products, including intelligent DMX moving heads, wireless battery operated DMX effects, static washes, sound-activated club effects, strobes & blacklights, LED lighting, fog and special effects machines, lasers and indoor and outdoor architectural lighting, as well as lighting controllers and protective bags.



BEAMZLIGHTING.COM