



BEAMZ
MADE
EAZY

150.638 V1.1

KRATOS TUBE70
QUICK **START GUIDE**

CONTROL MENU

MENU		DESCRIPTION			
DMX	001-512		DMX address setting		
SHOW	Auto	Auto Mode:000-068	68 kinds of Auto effect		
		Speed:001-016	1-16 from slow to fast on speed setting		
		Colour:000-015	Colour setting, 0 for automatic colour change, a total of 15 colours		
	Sound	Sound Mode:001-004	4 sound control modes optional		
		Sens:001-100	Sound sensitivity setting		
		Colour:000-015	Colour setting, 0 for automatic colour change, a total of 15 colours		
	Static Colour	Dimmer:000-255	Overall dimming		
		Strobe:000-255	Strobe		
		Red:000-255	Red dimming		
		Green:000-255	Green dimming		
		Blue:000-255	Blue dimming		
	Colour	Built in static colour	White:000-255	White dimming	
			Red	Cyan	Blue+W
			Green	Purple	Yellow+W
			Blue	Warm W	Cyan+W
			White	Red+W	Purple+W
	CCT	Colour temperature	Yellow	Green+W	Full
			2800K, 3000K, 3200K, 3500K, 3800K, 4000K, 4500K, 5000K, 5600K, 6000K, 6500K, 7000K, 7500K, 8000K, 8500K, 9000K, 9500K, 10000K		
	Wifi			On the phone, connect WIFI address "Led_XXX" and turn on the APP 【LED LAMP】 to control	
	SET	DMX channel	2CH/4CH/6CH/11CH/16CH/32CH/64CH		7 DMX channel modes
DMX fail		Hold / Blackout		Status of light fixture after DMX fail	
Display reverse		OFF / ON		Display Reverse OFF / ON	
Display on time		30S / 60S		Display start time	
Menu lock		OFF / ON		When Menu Lock is ON, the button will is locked after 30 seconds without any operation, and press the UP+DOWN button for 5 seconds to unlock.	
IR remote		OFF / ON		Infrared remote control OFF / ON	
Wireless 2.4g		Wireless	OFF / ON		
		Connect	NO / YES		
		Reset	NO / YES		
		Mode	Receive / Transmit		
Factory set		1.Red	000-255	Limit the red brightness value, factory default value is 200	
		2.Green	000-255	Limit the green brightness value, factory default value is 200	
		3.Blue	000-255	Limit the blue brightness value, factory default value is 200	
		4.White	000-255	Limit the white brightness value, factory default value is 200	

INFO	5.State		Single / Whole	Single: only the current colour, Whole: full colour working
	6.T.Limit		OFF / 040-100	Set the start temperature of temperature protection
	Factory reset	NO/ YES		YES: Restore factory settings
	Name	Kratos		
	Version	Vxxx		Software version

DMX CHANNELS

2 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	MASTER DIMMER	000-255	Master Dimmer 0-100%
2	No Function	000-010	CCT
	2800K	011-024	
	3000K	025-038	
	3200K	039-052	
	3500K	053-066	
	3800K	067-080	
	4000K	081-094	
	4500K	095-108	
	5000K	109-122	
	5600K	123-136	
	6000K	137-150	
	6500K	151-164	
	7000K	165-178	
	7500K	179-192	
	8000K	193-206	
	8500K	207-220	
	9000K	221-234	
	9500K	235-248	
	10000K	249-255	

4 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	RED	000-255	Dimmer Red 0-100%
2	GREEN	000-255	Dimmer Green 0-100%
3	BLUE	000-255	Dimmer Blue 0-100%
4	WHITE	000-255	Dimmer White 0-100%

6 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	MASTER DIMMRER	000-255	Master Dimmer 0-100%
2	STROBE	000-010	No Function
		011-255	Strobe from slow to fast
3	RED	000-255	Dimmer Red 0-100%
4	GREEN	000-255	Dimmer Green 0-100%
5	BLUE	000-255	Dimmer Blue 0-100%
6	WHITE	000-255	Dimmer White 0-100%

11 CHANNELS

CHANNELS	FUNCTION	VALUE	DESCRIPTION
1	MASTER DIMMRER	000-255	Master Dimmer 0-100%
2	STROBE	000-010	No Function
		011-255	Strobe from slow to fast
3	STATIC MACRO	000-010	No Function
		011-255	Static Macro
4	MACRO BACKGROUND Color	000-016	No Function
		017-255	Static Macro Background
5	MACRO BACKGROUND Color DIMMER	000-255	Linear Background Dimmer 0-100%

6	MACRO	000-010	No Function
		011-220	Macro effect
		221-228	Sound mode 1
		229-236	Sound mode 2
		237-244	No Function
		245-255	Sound mode 3
7	MACRO SPEED	000-255	Macro speed from slow to fast
8	RED	000-255	Dimmer Red 0-100%
9	GREEN	000-255	Dimmer Green 0-100%
10	BLUE	000-255	Dimmer Blue 0-100%
11	WHITE	000-255	Dimmer White 0-100%

16 CHANNELS

CHANNELS	FUNCTION	VALUE	DESCRIPTION
1	RED	000-255	Segment 1 Dimmer Red 0-100%
2	GREEN	000-255	Segment 1 Dimmer Green 0-100%
3	BLUE	000-255	Segment 1 Dimmer Blue 0-100%
4	WHITE	000-255	Segment 1 Dimmer White 0-100%
.....			
13	RED	000-255	Segment 4 Dimmer Red 0-100%
14	GREEN	000-255	Segment 4 Dimmer Green 0-100%
15	BLUE	000-255	Segment 4 Dimmer Blue 0-100%
16	WHITE	000-255	Segment 4 Dimmer White 0-100%

32 CHANNELS

CHANNELS	FUNCTION	VALUE	DESCRIPTION
1	RED	000-255	Segment 1 Dimmer Red 0-100%
2	GREEN	000-255	Segment 1 Dimmer Green 0-100%
3	BLUE	000-255	Segment 1 Dimmer Blue 0-100%
4	WHITE	000-255	Segment 1 Dimmer White 0-100%
.....			
29	RED	000-255	Segment 8 Dimmer Red 0-100%
30	GREEN	000-255	Segment 8 Dimmer Green 0-100%
31	BLUE	000-255	Segment 8 Dimmer Blue 0-100%
32	WHITE	000-255	Segment 8 Dimmer White 0-100%

64 CHANNELS

CHANNELS	FUNCTION	VALUE	DESCRIPTION
1	RED	000-255	Segment 1 Dimmer Red 0-100%
2	GREEN	000-255	Segment 1 Dimmer Green 0-100%
3	BLUE	000-255	Segment 1 Dimmer Blue 0-100%
4	WHITE	000-255	Segment 1 Dimmer White 0-100%
.....			
61	RED	000-255	Segment 16 Dimmer Red 0-100%
62	GREEN	000-255	Segment 16 Dimmer Green 0-100%
63	BLUE	000-255	Segment 16 Dimmer Blue 0-100%
64	WHITE	000-255	Segment 16 Dimmer White 0-100%







BEAMZ

YOUR FUTURE
YOUR SKILLS
YOUR PLATFORM
YOUR PARTY
YOUR EVENT

 **beamZ^{Pro}**

offers a wide range of high performance lighting equipment and related accessories for the rental, entertainment and architectural lighting markets. BeamZ Pro stands for performance, innovation and value pricing!



BEAMZLIGHTING.COM