



BEAMZ
MADE
EAZY

151.374 V1.4

BTS300Z

QUICK **START** GUIDE

CONTROL MENU

Menu			Description	
DMX Addr	d001-d512		DMX address setting	
Mode	DMX	1 / 2 / 3 Ch	DMX channel mode	
	Auto	Program	001-005	Preset programs
		Speed	001-009	Programs speed
	Manual	Dimmer	000-255	Dimmer 0-100%
		Strobe	000-255	Strobe, slow to fast
Dimmer	Curve	0.3-3.0	Dimmer curves adjustment	
	Mode	Standard	Select dimmer curve	
		Stage		
		TV		
		Architecture		
		Theatre		
		Studio		
		Custom	Fade in (150ms-2230ms)	
		Fade out (150ms-2230ms)		
Advance	Authorization	On / Off	Advanced settings for Beamz support only.	
	Signal hold	On / Off	Run if signal cut	
	RDM	On / Off	RDM function on / off	
	Screen Timeout	30sec.	Display shut off time	
		Never		
	Screen brightness	25-100%	Display brightness	
	Dimming Freq	1,2 Khz – 24,0 Khz	Dimmer frequency setting	
	Software Version	Vx.xx	Software version	
Reset	Yes / No	System reset		
Reverse	Yes / No	Display reverse 180°		

DMX CHANNELS

1 Channel

Channel	Function	Value	Description
1	Dimmer	000-255	Intensity 0-100%

2 Channel

Channel	Function	Value	Description
1	Dimmer	000-255	Intensity 0-100%
2	Strobe	000-013	No function
		014-255	Strobe, slow to fast

3 Channel

Channel	Function	Value	Description
1	Dimmer	000-255	Intensity 0-100%
2	Dimmer fine	000-255	Intensity 0-100%
3	Strobe	000-013	No function
		014-255	Strobe, slow to fast

European Union

Tronios B.V.,
Bedrijvenpark Twente Noord 18,
7602KR Almelo, The Netherlands

2014/35/EU
2014/30/EU
2011/65/EC



United Kingdom

Tronios Ltd.,
130 Harley Street,
London W1G 7JU, United Kingdom

S.I. 2016:1101
S.I. 2016:1091
S.I. 2012:3032





BEAMZ

YOUR FUTURE
YOUR SKILLS
YOUR PLATFORM
YOUR PARTY
YOUR EVENT

 **beamZ^{Pro}**

offers a wide range of high performance lighting equipment and related accessories for the rental, entertainment and architectural lighting markets. BeamZ Pro stands for performance, innovation and value pricing!



BEAMZLIGHTING.COM