



BEAMZ
MADE
EAZY

150.303 V1.0

MHL820 MKII

QUICK START GUIDE

CONTROL MENU

MENU		DESCRIPTION
ADDR	A001-A512	Address Setting
CHND	7CH	7 Channel option
	15CH	15 Channel option
SLND	MAST	Master option
	SLAV	Slave option
	Soun	Sound control selected
SHND	Sh1---sh24	Effect selected. Sh24 auto effect;SPED 01-08 speed from slow to fast
SOUD	ON,OFF	Sound control Switch
SENS	0-100	Sound Sensitivity(0 close,100 the most)
LED	OFF	Background Light Switch
	NO	Background Light Switch
DISP	NO	Reverse Display
	YES	Reverse Display
TIL1	NO	Y1 Motor reverse
	YES	Y1 Motor reverse
TIL2	NO	Y2 Motor reverse
	YES	Y2 Motor reverse
TEST		Automatically Test
RSET	YES,NO	Reset

DMX CHANNELS

7 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	MOTOR1 ROUTE	000-255	0° ---135°
2	MOTOR2 ROUTE	000-255	0° ---135°
3	SUM DIMMER	000-255	0---100%
4	STROBE	000-009	No Strobe
		010-255	Strobe speed from slow to fast
5	MACRO	000-007	No Effect
		008-017	Effect 1
		018-027	Effect 2
		028-037	Effect 3
		038-047	Effect 4
		048-057	Effect 5
		058-067	Effect 6
		068-077	Effect 7
		078-087	Effect 8
		088-097	Effect 9
		098-107	Effect 10
		108-117	Effect 11
		118-127	Effect 12
		128-136	Effect 13
		137-146	Effect 14
		147-156	Effect 15
		157-166	Effect 16
		167-176	Effect 17
		177-186	Effect 18
		187-196	Effect 19
		197-206	Effect 20
		207-216	Effect 21
		217-226	Effect 22
		227-236	Effect 23
		237-246	Effect 24 Self-propelled multi-effects
247-255	Effect 25 Sound		
6	EFFECT SPEED	000-255	From slow to fast
7	RESET	241-250	For 5 seconds to reset

15 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	MOTOR1 ROUTE	000-255	60° ---150°
2	MOTOR2 ROUTE	000-255	60° ---150°
3	SUM DIMMER	000-255	0---100%
4	STROBE	000-009	No strobe
		010-255	Strobe speed from slow to fast
5	LED1 DIMMING	000-255	0---100%
6	LED2 DIMMING	000-255	0---100%
7	LED3 DIMMING	000-255	0---100%
8	LED4 DIMMING	000-255	0---100%
9	LED5 DIMMING	000-255	0---100%
10	LED6 DIMMING	000-255	0---100%
11	LED7 DIMMING	000-255	0---100%
12	LED8 DIMMING	000-255	0---100%
13	MARCO FUNCTION	000-007	No Effect
		008-017	Effect 1
		018-027	Effect 2
		028-037	Effect 3
		038-047	Effect 4
		048-057	Effect 5
		058-067	Effect 6
		068-077	Effect 7
		078-087	Effect 8
		088-097	Effect 9
		098-107	Effect 10
		108-117	Effect 11
		118-127	Effect 12
		128-136	Effect 13
		137-146	Effect 14
		147-156	Effect 15
		157-166	Effect 16
		167-176	Effect 17
		177-186	Effect 18
		187-196	Effect 19
		197-206	Effect 20
		207-216	Effect 21
		217-226	Effect 22
227-236	Effect 23		
		237-246	Effect 24 Self-propelled multi-effects
		247-255	Effect 25 Sound
14	EFFECT SPEED	000-255	From slow to fast
15	RESET	241-250	For 5 seconds to reset



A series of horizontal dotted lines for writing, spanning the width of the page.



A series of horizontal dotted lines for writing, spanning the width of the page.





A series of horizontal dotted lines spanning the width of the page, providing a guide for handwriting practice.



BEAMZ

**YOUR FUTURE
YOUR SKILLS
YOUR PLATFORM
YOUR PARTY
YOUR EVENT**



is a leading developer of lighting products, including intelligent DMX moving heads, wireless battery operated DMX effects, static washes, sound-activated club effects, strobes & blacklights, LED lighting, fog and special effects machines, lasers and indoor and outdoor architectural lighting, as well as lighting controllers and protective bags.

