



BEAMZ
MADE
EAZY

150.711 V1.2

LCB99

QUICK START GUIDE

CONTROL MENU

MENU			DESCRIPTION
DMX	A001-Axxx		Auto-run mode
AUTO	Au1-32		Pre program
HOPPING	FF01-99		Program with hopping effect
FADE	CC01-99		Program with fade effect
JUMP	EE01-99		Program with jump effect
STROBE	F000-255		Strobe from slow to fast
COLOUR	r000-255		Red manual adjustment
	g000-255		Green manual adjustment
	b000-255		Blue manual adjustment
	u000-255		White manual adjustment
	y000-255		UV manual adjustment
AUTO	Auto		Auto run
SOUND	SOUD	uoL1-9	Sound sensitivity adjustment
		bAon / bAof	Sound mode on/off

DMX CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	Master dimmer	000-255	Dimming 0-100%
2		000-255	Red, 0-100%
3		000-255	Green, 0-100%
4	Colour	000-255	Blue, 0-100%
5		000-255	White, 0-100%
6		000-255	UV, 0-100%
7	Strobe	000-009	No function
		010-255	Strobe, slow to fast (CH1 must be on and select the colour CH2 till CH6)
8	Mode	000-010	No function
		011-070	Program with hopping effect
		071-130	Program with fade effect
		131-190	Program with pulse effect
		191-255	Sound mode
9	Speed	000-255	Control the speed/sensitivity of 8CH programs



BEAMZ

**YOUR FUTURE
YOUR SKILLS
YOUR PLATFORM
YOUR PARTY
YOUR EVENT**



is a leading developer of lighting products, including intelligent DMX moving heads, wireless battery operated DMX effects, static washes, sound-activated club effects, strobes & blacklights, LED lighting, fog and special effects machines, lasers and indoor and outdoor architectural lighting, as well as lighting controllers and protective bags.

