



**BEAMZ**  
**MADE**  
**EAZY**

151.306 & 151.313 V2.0

**BT270 & BT310**

**QUICK START GUIDE**

## CONTROL MENU

MENU		DESCRIPTION
<b>DMX Mode</b>	8 Ch	DMX address 8 channels
	4-1 Ch	DMX address 4 channels
	4 Ch	DMX address 4 channels
	3 Ch	DMX address 3 channels
	2 Ch	DMX address 2 channels
<b>Static colours</b>	S01-17	Static colours
<b>Auto</b>	Au 1-2	Auto program
<b>Sound</b>	So 1-2	Sound program
<b>Speed</b>	SP 1-9	Speed
<b>Mic Sensitivity</b>	SE 1-9	Mic sensitivity
<b>Edit colour</b>	R000-255	Red (0-100%)
	G000-255	Green (0-100%)
	B000-255	Blue (0-100%)
	U000-255	White (0-100%)
<b>Dimming</b>	D11- d19	Master dimming
<b>Silent scene</b>	On/Off	Silent scene by sound program
<b>Slave</b>	Slave	Slave function
<b>Infrared</b>	On/Off	Enable or disenable IR remote

## DMX CHANNELS

### 2 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	Master dimmer	000-255	Dimming all LED 0-100%
2	Static colour	000-009	No function
		010-019	Red
		020-029	Green
		030-039	Blue
		040-049	White
		050-059	Yellow
		060-069	Magenta
		070-079	Cyan
		080-089	Dark orange
		090-099	Green yellow
		100-109	Salmon
		110-119	Turquoise
		120-129	Light Green
		130-139	Orange
		140-149	Lavender
		150-159	Light blue
		160-169	Dark blue
170-255	Pink		

### 3 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	Colour	000-255	Red 0-100%
2		000-255	Green 0-100%
3		000-255	Blue 0-100%

#### 4 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	Colour	000-255	Red 0-100%
2		000-255	Green 0-100%
3		000-255	Blue 0-100%
4		000-255	White 0-100%

#### 4-1 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	Master dimmer	000-255	Dimming all LED 0-100%
2	Strobe	000-255	Stroboscope (Slow to fast)
3	Static colour	000-009	No function
		010-019	Red
		020-029	Green
		030-039	Blue
		040-049	White
		050-059	Yellow
		060-069	Magenta
		070-079	Cyan
		080-089	Dark orange
		090-099	Green yellow
		100-109	Salmon
		110-119	Turquoise
		120-129	Light Green
		130-139	Orange
		140-149	Lavender
		150-159	Light blue
		160-169	Dark blue
		170-255	Pink
4	Auto/ sound	000-009	No function
		010-069	Auto Color blending (rate)
		070-129	Auto Color change (rate)
		130-189	Sound color blending (rate)
		190-255	Sound color change (rate)

## 8 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION	
1	Master dimmer	000-255	Dimming all LED 0-100%	
2	Strobe	000-255	Stroboscope (Slow to fast)	
3	Colour	000-255	Red 0-100%	
4		000-255	Green 0-100%	
5		000-255	Blue 0-100%	
6		000-255	White 0-100%	
7		Static colour	000-009	No function
010-019			Red	
020-029	Green			
030-039	Blue			
040-049	White			
050-059	Yellow			
060-069	Magenta			
070-079	Cyan			
080-089	Dark orange			
090-099	Green yellow			
100-109	Salmon			
110-119	Turquoise			
120-129	Light Green			
130-139	Orange			
140-149	Lavender			
150-159	Light blue			
160-169	Dark blue			
170-255	Pink			
8	Colour macro	000-009	No function	
010-069		Auto Colour blending (rate)		
070-129		Auto Colour change (rate)		
130-189		Sound colour blending (rate)		
190-255		Sound colour change (rate)		



A series of horizontal dotted lines for writing, spanning the width of the page.



A series of horizontal dotted lines spanning the width of the page, intended for writing.





A series of horizontal dotted lines for writing, spanning the width of the page.



# BEAMZ

**YOUR FUTURE  
YOUR SKILLS  
YOUR PLATFORM  
YOUR PARTY  
YOUR EVENT**



is a leading developer of lighting products, including intelligent DMX moving heads, wireless battery operated DMX effects, static washes, sound-activated club effects, strobes & blacklights, LED lighting, fog and special effects machines, lasers and indoor and outdoor architectural lighting, as well as lighting controllers and protective bags.

