



BEAMZ
MADE
EAZY

153.602 V1.2

MULTIACE2

QUICK START GUIDE

CONTROL MENU

MENU		DESCRIPTION
ADDR	13CH	Select DMX start address d001-d512
	6CH	
	4CH	
	2CH	
STAT	S01-18	Static colours
AUTO	Au 1-3	Auto program
SOUN	So 1-3	Sound Program
SPEE	SP 1-9	Speed Program
SENS	SE 1-9	MIC sensitivity
COLO	r000-255	Red (0-100%)
	g000-255	Green (0-100%)
	b000-255	Blue (0-100%)
	u000-255	UV (0-100%)
SMD	smd	Edit intensity SMD(0-100%)
DIMM	dl 1- dl 9	Master dimming
SILE	on/oFF	Silent scene by Sound program
SLAV	Slave	Slave
INFR	on/oFF	Enable or Disenable IR remote

DMX CHANNELS

2 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	Dimmer	000-255	Master dimming (0-100%)
2	Colours	000-009	No function
		010-019	Red
		020-029	Green
		030-039	Blue
		040-049	UV
		050-059	Yellow
		060-069	Magenta
		070-079	Cyan
		080-089	Dark orange
		090-099	Green yellow
		100-109	Salmon
		110-119	Turquoise
		120-129	Light Green
		130-139	Orange
		140-149	Straw
		150-159	Lavender
		160-169	Light blue
170-179	Dark blue		
180-255	Pink		

4 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	Dimmer	000-255	Red (0-100%)
2	Dimmer	000-255	Green (0-100%)
3	Dimmer	000-255	Blue (0-100%)
4	Dimmer	000-255	UV (0-100%)

6 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION	
1	Dimmer	0-255	Master dimming (0-100%)	
2	Strobe Leds	0-255	Stroboscope (Rate 0-100%)	
		Color	0-9	No function
			10-19	Red
			20-29	Green
			30-39	Blue
			40-49	UV
			50-59	Yellow
			60-69	Magenta
			70-79	Cyan
			80-89	Dark orange
			90-99	Green yellow
			100-109	Salmon
			110-119	Turquoise
			120-129	Light Green
			130-139	Orange
			140-149	Straw
			150-159	Lavender

		160-169	Light blue
		170-179	Dark blue
		180-255	Pink
4	Strobe SMD Leds	0-255	Stroboscope SMD (Rate 0-100%)
5	Dimmer	0-255	SMD (0-100%)
6	Auto programs	0-9	No function
		10-49	Auto program1
		50-89	Auto program2
		90-129	Auto program3
		130-169	Sound program1
		170-209	Sound program2
		210-255	Sound program3

13 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	Dimmer	0-255	Master dimming (0-100%)
2	Strobe function	0-255	Stroboscope (Rate 0-100%)
3	Dimmer	0-255	Red (0-100%)
4	Dimmer	0-255	Green (0-100%)
5	Dimmer	0-255	Blue (0-100%)
6	Dimmer	0-255	UV (0-100%)
7	Color picker	0-9	No function
		10-19	Red
		20-29	Green
		30-39	Blue
		40-49	UV
		50-59	Yellow
		60-69	Magenta
		70-79	Cyan
		80-89	Dark orange
		90-99	Green yellow
		100-109	Salmon
		110-119	Turquoise
		120-129	Light Green
		130-139	Orange
		140-149	Straw
		150-159	Lavender
		160-169	Light blue
170-179	Dark blue		
180-255	Pink		
8	Strobe function SMD	0-255	Stroboscope SMD (Rate 0-100%)
9	Dimmer	0-255	SMD1
10	Dimmer	0-255	SMD2
11	Dimmer	0-255	SMD3
12	Dimmer	0-255	SMD4
13	Auto programs	0-9	No function
		10-49	Auto program1
		50-89	Auto program2
		90-129	Auto program3
		130-169	Sound program1
		170-209	Sound program2
		210-255	Sound program3



A series of horizontal dotted lines for writing, spanning the width of the page.



A series of horizontal dotted lines for writing, spanning the width of the page.





A series of horizontal dotted lines spanning the width of the page, intended for writing or drawing.



BEAMZ

**YOUR FUTURE
YOUR SKILLS
YOUR PLATFORM
YOUR PARTY
YOUR EVENT**



is a leading developer of lighting products, including intelligent DMX moving heads, wireless battery operated DMX effects, static washes, sound-activated club effects, strobes & blacklights, LED lighting, fog and special effects machines, lasers and indoor and outdoor architectural lighting, as well as lighting controllers and protective bags.

