



**BEAMZ**  
**MADE**  
**EAZY**

150.780, 150.782, 150.784 V1.2

**WBP SERIES PAR**  
**QUICK **START** GUIDE**

# CONTROL MENU

## MENU

<b>PRESET</b>	ID	0-39	Static colours	
	Master	0-100	Master dimmer 0-100%	
	Red	0-255	Red dimmer 0-100%	
	Green	0-255	Green dimmer 0-100%	
	Blue	0-255	Blue dimmer 0-100%	
	White	0-255	White dimmer 0-100%	
	Amber	0-255	Amber dimmer 0-100%	
	UV	0-255	Purple dimmer 0-100%	
<b>COLOUR</b>	ID	0-63	Static colours	
	Master	0-100	Master dimmer 0-100%	
<b>EFFECTS</b>	Chase	Built-in	0-9	
			ID:0-7	
			Add Scene	Red
				Green
				Blue
				White
				Amber
				UV
			Delete Scene	
			Fading	
			Jumping	
			Pulse	
		Master	0-100	Master dimmer 0-100%
	Speed	0-255	Selectable speed	
	Fade	0-100		
<b>STROBE</b>	Strobe	0-255		
	Colour	0-100	Master	
		0-255	Red	
		0-255	Green	
		0-255	Blue	
		0-255	White	
		0-255	Amber	
		0-255	UV	
<b>SOUND</b>	Sound enable	On / Off		
	Sensitivity	0-9		
	Brightness	0-9		
<b>SETTINGS</b>	DMX	DMX Address	000-512	
		Master/Slave	Master / Slave	
		Channel mode	Normal / Simple	
		When no DMX	Off / Hold / Power up / Last	
	Wireless	Wireless En	Off / On	
	Display	Screen mode	Status / On / Off / Logo	
		Screen time	Off time	
		Wireless LED	On / Off	

## MENU

SETTINGS	General	Power-up	Preset	0-39	Selectable effects
			Colour	0-63	Selectable effects
			Chase	0-20	Selectable effects
			Last set		
		Battery Mode	Bright / Normal / Life		
		Dim Response	LEDs / Fast / Less fast / Middle / Slow		
		Dimming curve	Linear / LOG / S Curve / Exp		
		RDM Enable	On / Off		
		RF Enable	On / Off		
		Power Off BAT	0-50 %		
		Top Temp	25-85 degrees		
	Password	Password	On / Off		
		Set Password	Please enter the factory password first: <b>MENU -UP-ENTER-DOWN</b> , Then enter your new password.		
	Time	Time	Enter the actual time		
		Power ON	Switch on fixture on time, start		
		Power OFF	Switch off fixture on time		
	Load Factory	MENU	Cancel		
		ENTER	Reset		
<b>STATUS</b>	LED Current	Master	0-100		
		Red	0-100		
		Green	0-100		
		Blue	0-100		
		White	0-100		
		Amber	0-100		
		UV	0-100		
	Temperature				
	Battery Voltage				
	DMX Channel				
	RDM UID1				
	RDM UID2				
	Software : BAT-6S02				
	Version: MAY 04 2022				

# DMX CHANNELS

## D001

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	Colour	000-255	Red, 0-100%
2		000-255	Green, 0-100%
3		000-255	Blue, 0-100%
4		000-255	White, 0-100%
5		000-255	Amber, 0-100%
6		000-255	UV, 0-100%

## A001

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	Master	000-255	Master dimmer, 0-100%
2	Colour	000-255	Red, 0-100%
3		000-255	Green, 0-100%
4		000-255	Blue, 0-100%
5		000-255	White, 0-100%
6		000-255	Amber, 0-100%
7		000-255	UV, 0-100%
8		Strobe	000-005
	006-255		Strobe, from slow to fast
9	Preset colours	000-010	No function
		011-127	40 preset colours
		128-129	No function
		130-255	64 factory colours
10	Mode	000-019	No function
		020-079	18 Chases
		080-127	Custom chases
		128-159	63 Colour fade
		128-159	63 Colour fade
		160-191	63 Colour jump
		192-223	63 Colour pulse
		224-255	Sound control
11	Speed	000-255	Speed, from slow to fast
12	Dimmer curve	000-005	No function
		006-055	Dimmer response, LEDs
		056-105	Dimmer response, Fast
		106-155	Dimmer response, Less fast
		156-205	Dimmer response, Middle
	206-255	Dimmer response, Slow	

# TECHNICAL SPECIFICATIONS

	<b>WBP612IP 150.780</b>	<b>WBP912IP 150.782</b>	<b>WBP1212IP 150.784</b>
Rated voltage :	100-240VAC, 50-60Hz, 0.4-0.2A	100-240VAC, 50-60Hz, 0.7-0.35A	100-240VAC, 50-60Hz, 0.5-0.3A
LED :	6x 12Watt, 6-in-1 LED	9x 12Watt, 6-in-1 LED	12x 12Watt, 6-in-1 LED
LED Colour :		Red, Green, Blue, Amber, White and Ultra Violet	
Beam angle :	25-44°	17-39°	18-39°
Illuminance :	8.140lx @1m	7.563lx @1m	13.000lx @1m
DMX Channels :		6, 12	
IP classification :		IP65	
Built-in battery :	Lithium battery 10.4Ah/12.6Volt	Lithium battery 16Ah/12.6Volt	Lithium battery 19.2Ah/12.6Volt
Functions :		DMX, Automatic programs, Sound to light and Master-Slave	
Dimensions per unit :	170 x 230 x 210mm	215 x 280 x 235mm	270 x 140 x 280mm
Weight (per unit) :	3,80kg	5,15kg	5,15kg

Design and product specifications are subject to change without prior notice.

## European Union

Tronios B.V.,  
Bedrijvenpark Twente Noord 18,  
7602KR Almelo, The Netherlands

2014/35/EU  
2014/30/EU  
2011/65/EC



## United Kingdom

Tronios Ltd.,  
130 Harley Street,  
London W1G 7JU, United Kingdom

S.I. 2016:1101  
S.I. 2016:1091  
S.I. 2012:3032





A series of horizontal dotted lines for writing, spanning the width of the page.





A series of horizontal dotted lines for writing, spanning the width of the page.





# BEAMZ

**YOUR FUTURE  
YOUR SKILLS  
YOUR PLATFORM  
YOUR PARTY  
YOUR EVENT**



is a leading developer of lighting products, including intelligent DMX moving heads, wireless battery operated DMX effects, static washes, sound-activated club effects, strobes & blacklights, LED lighting, fog and special effects machines, lasers and indoor and outdoor architectural lighting, as well as lighting controllers and protective bags.

