



BEAMZ
MADE
EAZY

150.709 V1.0

LCB14C

QUICK START GUIDE

CONTROL MENU

MENU		DESCRIPTION
Addr	A001-A512	DMX start address
ChNd	8 Ch	DMX channel mode
	11 Ch	
	32 Ch	
	98 Ch	
SLNd	Mast	Working mode
	SLAU	
SoUn	Su0-Su59	Sound control
	Se00-Se99	Sensitivity setting
Auto	Au0-Au59	Auto mode
	SP1-SP9	Speed setting
dISP	dSIP	Display reverse
Ver	Vxx	Software version

DMX CHANNELS

8 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	MASTER DIMMER	000-255	Master dimmer 0-100%
2	STROBE	000-255	Strobe from slow to fast
3	RED	000-255	Dimmer Red 0-100%
4	GREEN	000-255	Dimmer Green 0-100%
5	BLUE	000-255	Dimmer Blue 0-100%
6	WHITE	000-255	Led Dimmer White 0-100%
7	PROGRAM	000-007	No Function
		008-247	Built-in programs (See table 1)
		248-255	Sound control
8	SPEED	000-255	Program speed slow to fast

11 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	MASTER DIMMER	000-255	Dimmer 0-100%
2	STROBE	000-255	Strobe from slow to fast
3	BACKGROUND RED	000-255	Background Dimmer Red 0-100%
4	BACKGROUND GREEN	000-255	Background Dimmer Green 0-100%
5	BACKGROUND BLUE	000-255	Background Dimmer Blue 0-100%
6	RED	000-255	Dimmer Red 0-100%
7	GREEN	000-255	Dimmer Green 0-100%
8	BLUE	000-255	Dimmer Blue 0-100%
9	WHITE	000-255	Dimmer White 0-100%
10	PROGRAM	000-007	No Function
		008-247	Built-in programs (See table 1)
		248-255	Sound control
11	SPEED	000-255	Program speed slow to fast

32 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	MASTER DIMMER	000-255	Dimmer
2	STROBE	000-255	Strobe from slow to fast

3	BACKGROUND COLOUR	000-015	No Function
		016-255	Background colour selection segment 1 (see table 2)
4	BACKGROUND COLOUR	000-015	No Function
		016-255	Background colour selection segment 2 (see table 2)
.....			
16	BACKGROUND COLOUR	000-015	No Function
		016-255	Background colour selection segment 2 (see table 2)
17	COLOUR	000-015	No Function
		016-255	Colour selection Led 1 (see table 2)
18	COLOUR	000-015	No Function
		016-255	Colour selection Led 2 (see table 2)
.....			
30	COLOUR	000-015	No Function
		016-255	Colour selection Led 14 (see table 2)
31	PROGRAM	000-007	No function
		008-247	Built-in programs (See table 1)
		248-255	Sound control
32	SPEED	000-255	Speed slow to fast

98 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	BACKGROUND RED	000-255	Segment 1 Background Dimmer Red 0-100%
2	BACKGROUND GREEN	000-255	Segment 1 Background Dimmer Green 0-100%
3	BACKGROUND BLUE	000-255	Segment 1 Background Dimmer Blue 0-100%
4	BACKGROUND RED	000-255	Segment 2 Background Dimmer Red 0-100%
5	BACKGROUND GREEN	000-255	Segment 2 Background Dimmer Green 0-100%
6	BACKGROUND BLUE	000-255	Segment 2 Background Dimmer Blue 0-100%
.....			
40	BACKGROUND RED	000-255	Segment 14 Background Dimmer Red 0-100%
41	BACKGROUND GREEN	000-255	Segment 14 Background Dimmer Green 0-100%
42	BACKGROUND BLUE	000-255	Segment 14 Background Dimmer Blue 0-100%
43	RED	000-255	Led 1 Dimmer Red 0-100%
44	GREEN	000-255	Led 1 Dimmer Green 0-100%
45	BLUE	000-255	Led 1 Dimmer Blue 0-100%
46	WHITE	000-255	Led 1 Dimmer White 0-100%
47	RED	000-255	Led 2 Dimmer Red 0-100%
48	GREEN	000-255	Led 2 Dimmer Green 0-100%
49	BLUE	000-255	Led 2 Dimmer Blue 0-100%
50	WHITE	000-255	Led 2 Dimmer White 0-100%
.....			
95	RED	000-255	Led 14 Dimmer Red 0-100%
96	GREEN	000-255	Led 14 Dimmer Green 0-100%
97	BLUE	000-255	Led 14 Dimmer Blue 0-100%
98	WHITE	000-255	Led 14 Dimmer White 0-100%

TABLE 1				TABLE 2	
000-007	No function	126-129	Program 30	000-015	No function
008-012	Program 1	130-133	Program 31	016-031	Colour1
013-016	Program 2	134-137	Program 32	032-047	Colour2
017-020	Program 3	138-141	Program 33	048-063	Colour3
021-024	Program 4	142-145	Program 34	064-079	Colour4
025-028	Program 5	146-149	Program 35	080-095	Colour5
029-032	Program 6	150-153	Program 36	096-111	Colour6
033-036	Program 7	154-158	Program 37	112-127	Colour7
037-040	Program 8	159-162	Program 38	128-143	Colour8
041-044	Program 9	163-167	Program 39	144-159	Colour9
045-048	Program 10	168-170	Program 40	160-175	Colour10
049-052	Program 11	171-174	Program 41	176-191	Colour11
053-056	Program 12	175-178	Program 42	192-207	Colour12
057-060	Program 13	179-182	Program 43	208-223	Colour13
061-064	Program 14	183-186	Program 44	224-239	Colour14
065-068	Program 15	187-190	Program 45	240-255	Colour15
069-072	Program 16	191-194	Program 46		
073-076	Program 17	195-198	Program 47		
077-080	Program 18	199-202	Program 48		
081-085	Program 19	203-206	Program 49		
086-089	Program 20	207-210	Program 50		
090-093	Program 21	211-214	Program 51		
094-097	Program 22	215-218	Program 52		
098-101	Program 23	219-222	Program 53		
102-105	Program 24	223-226	Program 54		
106-109	Program 25	227-231	Program 55		
110-113	Program 26	232-235	Program 56		
114-117	Program 27	236-239	Program 57		
118-121	Program 28	240-243	Program 58		
122-125	Program 29	244-247	Program 59		









BEAMZ

YOUR FUTURE
YOUR SKILLS
YOUR PLATFORM
YOUR PARTY
YOUR EVENT



is a leading developer of lighting products, including intelligent DMX moving heads, wireless battery operated DMX effects, static washes, sound-activated club effects, strobes & blacklights, LED lighting, fog and special effects machines, lasers and indoor and outdoor architectural lighting, as well as lighting controllers and protective bags.



BEAMZLIGHTING.COM